



9210-125
Reference booklet

Sample

Properties of the Fourier Transform

Property	Aperiodic signal	Fourier transform
	$x(t)$	$X(j\omega)$
	$y(t)$	$Y(j\omega)$
Linearity	$ax(t) + by(t)$	$aX(j\omega) + bY(j\omega)$
Time shifting	$x(t - t_0)$	$e^{-j\omega t_0}X(j\omega)$
Time shifting	$e^{j\omega_0 t}x(t - t_0)$	$X(j(\omega - \omega_0))$
Conjugation	$x^*(t)$	$X^*(-j\omega)$
Time reversal	$x(-t)$	$X(-j\omega)$
Time and frequency scaling	$x(at)$	$\frac{1}{ a }X\left(\frac{j\omega}{a}\right)$
Convolution	$x(t) * y(t)$	$X(j\omega)Y(j\omega)$
Multiplication	$x(t)y(t)$	$\frac{1}{2\pi}X(j\omega) * Y(j\omega)$
Differentiation in time	$\frac{d}{dt}x(t)$	$j\omega X(j\omega)$
Integration	$\int_{-\infty}^t x(t)dt$	$\frac{1}{j\omega}X(j\omega) + \pi X(0)\delta(\omega)$
Differentiation in frequency	$tx(t)$	$j \frac{d}{d\omega}X(j\omega)$

Basic Fourier Transform Pairs

Signal	Fourier transform
$\sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta(\omega - k\omega_0)$
$e^{j\omega t}$	$2\pi\delta(\omega - \omega_0)$
$\cos \omega_0 t$	$\pi[\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$
$\sin \omega_0 t$	$\frac{\pi}{j} [\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$
$x(t) = 1$	$2\pi\delta(\omega)$
$\delta(t)$	1
$u(t)$	$\frac{1}{j\omega} + \pi\delta(\omega)$
$\delta(t - t_0)$	$e^{-j\omega t_0}$